

# SEMICONDUCTOR DEVICE HAVING BOTH MEMORY AND LOGIC CIRCUIT AND ITS MANUFACTURE

This application is based on Japanese patent application HEI 10-281699  
5 filed on October 2, 1998, the whole contents of which are incorporated herein by  
reference.

## BACKGROUND OF THE INVENTION

### a) Field of the Invention

10 The present invention relates to a semiconductor device and its  
manufacture method, and more particularly to a semiconductor device having memory  
cells and logic circuits both formed on the same substrate, and its manufacture method.

### b) Description of the Related Art

15 In a semiconductor device formed with both dynamic random access  
memories (DRAM) and logic circuits, a metal silicide film is formed on the source/drain  
regions and gate electrode of a MISFET in a the logic circuit area in order to improve the  
performance of logic circuits.

In order to improve the data storage characteristics of memory cells of a  
semiconductor device such as DRAM, it is desired to reduce junction leak current of  
20 source/drain regions. If a metal silicide film is formed on the source/drain regions, the  
junction leak current increases (refer to The 178-th Meeting, the Electro-chemical Society,  
pp. 218 to 220). Therefore, the metal silicide film is not formed generally during  
manufacture processes of DRAM.

In a semiconductor device formed with both DRAM and logic circuits, it is  
25 desired that a metal silicide film is not formed in the DRAM area but it is formed only in  
the logic circuit area.

10500-49212-0001  
10  
5  
In the DRAM area, the gate electrode of MISFET constituting a memory cell is generally formed integrally with a word line. In order to lower the resistance of the word line made of polysilicon or the like, it is desired to dope impurities at a high concentration. In the logic circuit area, however, a proper impurity concentration is determined from the threshold value or the like of MISFET. Therefore, the optimum impurity concentrations of the gate electrodes in the memory cell area and logic circuit area are not always coincident.

A precision of an electrostatic capacitance value of a capacitor in an analog circuit in the logic circuit area is desired to be made higher. From this reason, generally

a three-layer structure of a polysilicon film / a silicon oxide film / a polysilicon film is used.

10  
15  
In order to reduce the voltage dependency of a capacitor, it is preferable to make the polysilicon film have a high impurity concentration. In order to suppress an increase in a manufacture cost, it is desired to suppress as much as possible an increase in the number of manufacture processes necessary for forming a polysilicon film of a high impurity concentration.

20  
A method is known by which after only the memory cell area is formed, the logic circuit area is formed. If a bit line is disposed under the cell plate which is used as a common electrode of capacitors constituting memory cells, it is necessary that the front end of the bit line protrudes from the boarder of the cell plate in order to electrically connect the bit line and a wiring pattern in the logic circuit area. A process of removing an interlayer insulating film deposited in the logic circuit and a process of patterning a cell plate are therefore required to be executed separately when memory cells are formed.

## SUMMARY OF THE INVENTION

25  
It is an object of the present invention to provide a semiconductor device and its manufacture method capable of improving the electric characteristics of a logic

circuit area while the data storage characteristics of memory cells are maintained good.

It is another object of the present invention to provide a semiconductor device formed with both DRAM and memory circuits and its manufacture method, capable of forming capacitors in the logic circuit area while an increase in the number of manufacture processes is suppressed.

It is a further object of the invention to provide a semiconductor device and its manufacture method capable of electrically connecting a bit line in the memory cell area to a wiring pattern in the logic circuit area while an increase in the number of manufacture processes is suppressed when only the memory cell area is formed before the logic circuit area is formed.

According to one aspect of the present invention, there is provided a method of manufacturing a semiconductor device comprising the steps of: preparing a semiconductor substrate having a memory cell area and a logic circuit area defined on a principal surface of the semiconductor substrate; forming a gate insulating film on the principal surface of the semiconductor substrate; forming a silicon film on the gate insulating film; doping impurities into the silicon film to make a region of the silicon film in the memory cell area have a first impurity concentration and to make a region of the silicon film in the logic circuit area have a second impurity concentration lower than the first impurity concentration; patterning the silicon film to leave word lines having the first impurity concentration and serving as gate electrodes in the memory cell area and to leave gate electrodes having the second impurity concentration in the logic circuit area; and forming source/drain regions of MISFET's in a surface layer of the semiconductor substrate by doping impurities into regions on both sides of each word line in the memory cell area and into regions on both sides of each gate electrode in the logic circuit.

Since the impurity concentration of word lines in the memory cell area is relatively high, the resistance of the word line can be lowered. Since the impurity

concentration of gate electrodes of MISFET's in the logic circuit area is relatively low, the electrical characteristics of MISFET's can be improved.

According to another aspect of the present invention, there is provided a semiconductor device comprising: a semiconductor substrate having a memory cell area and a logic circuit area defined on a principal surface of the semiconductor substrate; a plurality of memory cells disposed in the memory cell area of the semiconductor substrate, each memory cell including a first MISFET and a capacitor, and a gate electrode of each first MISFET having a first impurity concentration; and a plurality of second MISFET's disposed in the logic circuit area of the semiconductor substrate, each second MISFET having a conductivity type same as a conductivity type of the first MISFET and a gate electrode of each second MISFET having a second impurity concentration lower than the first impurity concentration.

Since the impurity concentration of gate electrodes of MISFET's in the memory cell area is relatively high, the resistance of the word line serving also as the gate electrode can be lowered. Since the impurity concentration of gate electrodes of MISFET's in the logic circuit area is relatively low, the electrical characteristics of MISFET's can be improved.

According to another aspect of the present invention, there is provided a method of manufacturing a semiconductor device comprising the steps of: preparing a semiconductor substrate having a memory cell area and a logic circuit area defined on a principal surface of the semiconductor substrate; forming an element separation structure made of insulating material in a partial area of the principal surface of the semiconductor substrate to define active regions; forming first gate insulating films in areas of the principal surface of the semiconductor substrate where the element separation structure is not formed; forming a first conductive film covering the element separation structure and the first gate insulating films; removing the first conductive film

in the memory cell area; forming a capacitor dielectric film on a surface of the first  
conductive film; forming a second conductive film on the capacitor dielectric film and on  
the semiconductor substrate; patterning the second conductive film to leave an upper  
electrode over the element separation structure and to leave a plurality of word lines  
5 serving as gate electrodes in the memory cell area; and patterning the capacitor dielectric  
film and the first conductive film to leave a lower electrode made of the first conductive  
film, in which the lower electrode is left in a shape inclusive of the upper electrode as  
viewed along a direction normal to the semiconductor substrate, a gate electrode made of  
the first conductive film is left over the active region in the logic circuit area, and the  
10 capacitor dielectric film is left between the upper and lower electrodes.

The upper electrode of capacitors and the word lines are formed at the  
same time, and the lower electrodes and the gate electrodes in the logic circuit area are  
formed at the same time. It is therefore possible to form capacitors while an increase in  
the number of manufacture processes is suppressed.

According to another aspect of the present invention, there is provided a  
semiconductor device comprising: a semiconductor substrate having a memory cell area  
and a logic circuit area defined on a principal surface of the semiconductor substrate, and  
element separation structures formed on surfaces of the logic circuit area and the  
memory cell area; a plurality of memory cells disposed on the semiconductor substrate in  
15 the memory cell area, each memory cell including a first MISFET and a capacitor and a  
gate electrode of the first MISFET having a first structure; a plurality of second  
MISFETs disposed on the semiconductor surface in the logic circuit area, each second  
MISFET having a same conductivity type as a conductivity type of the first MISFET and  
a gate of the second MISFET having a second structure; and a capacitor disposed on the  
20 element separation structure in the logic circuit area, the capacitor having a lower  
electrode, a capacitor dielectric film, and an upper electrode stacked in this order,

wherein the upper electrode has the first structure and the lower electrode has the second structure.

According to another aspect of the present invention, there is provided a semiconductor device comprising: MISFET's formed on a surface of a semiconductor substrate, each MISFET including source/drain regions and a gate electrode disposed above a channel region between the source/drain regions; a cover insulating film made of insulating material and covering an upper and side surfaces of the gate electrode; a conductive pad disposed covering a corresponding upper surface of the source/drain regions and corresponding side surfaces of the cover insulating films; an interlayer insulating film disposed over the semiconductor substrate and covering the pad and the MISFET's; a contact hole formed in the interlayer insulating film at a position included by the pad as viewed along a direction normal to the semiconductor substrate; and a capacitor formed on the interlayer insulating film, one electrode of the capacitor being connected via the contact hole to the pad.

When the contact hole is formed, the pad is exposed and the underlying source/drain regions are not exposed. Since the source/drain regions are not exposed to the etching atmosphere of etching the interlayer insulating film, damages to the source/drain regions can be avoided.

According to another aspect of the present invention, there is provided a method of manufacturing a semiconductor substrate comprising the steps of: preparing a semiconductor substrate having a memory cell area and a logic circuit area defined on a principal surface of the semiconductor substrate; forming a DRAM circuit on the semiconductor substrate in the memory cell area, wherein the DRAM circuit includes a plurality of memory cells and bit lines, each memory cell has a pair of MISFET and capacitor, one electrode of the capacitor is connected to one region of source/drain regions of a corresponding MISFET, the bit line interconnects the other regions of source/drain

regions of MISFET's of some memory cells, the bit line extends near to a boarder line between the memory cell area and the logic circuit area, the other opposing electrode of the capacitor is disposed on a layer higher than the bit line and connected to a plurality of capacitors, a first insulating film electrically insulates the bit lines and MISFET's, a second insulating film electrically insulates the bit lines and capacitors, and the opposing electrode and first and second insulating films are also disposed in the logic circuit area; covering a surface of the opposing electrode in the memory cell area with a resist pattern, wherein a boarder of the resist pattern is positioned apart from a front end of the bit lines toward the logic circuit area; isotropically etching the opposing electrode to remove the opposing electrode in the logic circuit area, by using the resist pattern as a mask, wherein the opposing electrode in the logic circuit area is also side-etched until a border of the opposing electrode retracts from the front end of the bit line; etching and removing the first and second interlayer insulating films in the logic circuit area by using the resist pattern as a mask; covering a whole surface of the semiconductor substrate with a third interlayer insulating film; forming a contact hole in the third and second interlayer insulating films, the contact hole being formed at a position away from the boarder of the opposing electrode toward the logic circuit area and exposing a partial upper surface of the bit line; and forming a wiring on the third insulating film, the wiring being connected via the contact hole to the bit line and extending in the logic circuit area.

Since the opposing electrode is side-etched through isotropic etching, the boarder of the opposing electrode can be retracted from the boarder line between the logic circuit area and memory cell area. It is therefore easy to connect the wiring in the logic circuit area to the bit line.

According to another aspect of the present invention, there is provided a semiconductor device comprising: a semiconductor substrate having a memory cell area and a logic circuit area defined on a principal surface of the semiconductor substrate; an

element separation structure formed on the semiconductor substrate in a boarder area between the memory cell area and the logic circuit area; an interconnect wiring disposed on the element separation structure; a DRAM circuit formed on the semiconductor substrate in the memory cell area, wherein the DRAM circuit includes a plurality of memory cells and bit lines, each memory cell has a pair of MISFET and capacitor, one electrode of the capacitor is connected to one region of source/drain regions of a corresponding MISFET, the bit line interconnects the other regions of source/drain regions of MISFET's of some memory cells, the bit line extends near to a boarder line between the memory cell area and the logic circuit area, and the bit line is disposed on a layer higher than the interconnect wiring and connected thereto; an interlayer insulating film covering the DRAM circuit and the logic circuit area; a contact hole formed through the interlayer insulating film, a bottom of the contact hole being a partial upper surface of the interconnect wiring; and an upper wiring disposed on the interlayer insulating film, the upper wiring being connected via the contact hole to the interconnect wiring and extending in the logic circuit area.

Although the boarder of the opposing electrode is generally flush with the boarder line between the logic circuit area and memory cell area, the interconnect wiring connected to the bit line extends to the logic circuit area. By connecting the wiring in the logic circuit area to the interconnect wiring, the wiring in the logic circuit area can be connected to the bit line.

As above, in DRAM mixed with logic circuits, the impurity concentrations of gate electrodes of MISFET's in the memory cell area and logic circuit area are set to proper values so that both the data storage characteristics of DRAM and the electrical characteristics of logic circuits can be improved.

The lower electrode of a capacitor in the logic circuit area and the gate electrode of MISFET in the logic circuit area are formed at the same time, and the upper



electrode and the word line in the memory cell area are formed at the same time. It is therefore possible to suppress an increase in the number of manufacture processes.

The opposing electrode in the memory cell area is isotropically etched to retract the boarder of the opposing electrode from the boarder line between the memory cell area and logic circuit area. It is therefore unnecessary to use a photomask for defining the boarder of the opposing electrode.

The wiring in the logic circuit area is connected to the bit line in the memory cell area via the interconnect wiring disposed on the element separation structure formed on a boarder area between the logic circuit area and memory cell area.

By making the interconnect wiring extend away from the boarder of the opposing electrode in the memory cell area toward the logic circuit area, it becomes easy to connect the wiring in the logic circuit area to the interconnect wiring.

## DESCRIPTION OF THE DRAWINGS

Figs. 1A to 1I are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to a first embodiment of the invention.

Fig. 2A is a graph showing a relation between an impurity dose in a gate electrode and a drain current of MISFET, and Fig. 2A is a graph showing a relation between an impurity dose in a gate electrode and a sheet resistance.

Figs. 3A to 3E are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to a second embodiment of the invention.

Figs. 4A to 4F are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to a third embodiment of the invention.

Figs. 5A and 5B are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to a fourth embodiment of the invention.

Figs. 6A and 6B are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to a fifth embodiment of the invention.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

With reference to Figs. 1A to 1I and Figs. 2A and 2B, the first embodiment of the invention will be described. Figs. 1A and 1I are cross sectional views of a substrate illustrating a method of manufacturing a semiconductor device according to the fifth embodiment. In each drawing, the left side of a cut portion shows a memory cell area, and the right side shows an n-channel MISFET forming area in the logic circuit area.

Processes up to the process illustrated in Fig. 1A will be described first. On the surface of a p-type silicon substrate 1, element separation structures 2 of a shallow trench type are formed by a well-known method. The element separation structures 2 define an active region 3 in the memory cell array area and an active region 4 in the logic circuit area. On the surfaces of the active regions 3 and 4, gate oxide films 7 of  $\text{SiO}_2$  are formed to a thickness of 5 to 10 nm through thermal oxidation. A polysilicon film 8 is deposited to a thickness of 100 to 250 nm, covering the gate oxide film 7. For example, the polysilicon film 8 is deposited through chemical vapor deposition (CVD) using  $\text{SiH}_4$ .

The polysilicon film 8 is subject to a first phosphorous (P) ion implantation under the conditions of an acceleration energy of 10 to 30 keV and a dose of 3 to 6 x  $10^{15} \text{cm}^{-2}$ . In this case, the p-channel MISFET forming area (not shown) in the logic

circuit area is covered with a resist pattern.

As shown in Fig. 1B, the surface of the polysilicon film 8 in the logic circuit area is covered with a resist pattern 5. The polysilicon film 8 in the memory cell area is subject to a second P ion implantation under the conditions of an acceleration energy of 10 to 30 keV and a dose of  $5 \text{ to } 8 \times 10^{15} \text{ cm}^{-2}$ . After this ion implantation, the resist pattern 5 is removed.

As shown in Fig. 1C, the polysilicon film 8 is patterned to leave a plurality of word lines 8a in the memory cell area and gate electrodes 8b in the logic circuit. For example, the polysilicon film 8 is etched through reactive ion etching (RIE) using a mixture gas of  $\text{Cl}_2$  and  $\text{O}_2$ . The word line 8a extends vertically relative to the surface of the drawing sheet. Two word lines 8a traverse on one active region 3. The word lines 8a are also formed on the element separation structures 2 on both sides of the active region 3. The word lines 8a on the active region 3 also serve as the gate electrodes of MISFET's to be formed in the active region 3.

By using the word lines 8a and gate electrode 8b as a mask, impurity ions are implanted. P ions are implanted in the MISFET forming area in the memory cell area under the conditions of an acceleration energy of 10 to 30 keV and a dose of  $1 \text{ to } 5 \times 10^{15} \text{ cm}^{-2}$ . P ions are implanted in the n-channel MISFET forming area in the logic circuit area under the conditions of an acceleration energy of 5 to 30 keV and a dose of  $1 \text{ to } 5 \times 10^{15} \text{ cm}^{-2}$ , and then As ions are doped in the same area under the conditions of an acceleration energy of 5 to 30 keV and a dose of  $1 \text{ to } 50 \times 10^{13} \text{ cm}^{-2}$ . With these ion implantation processes, source/drain regions 9a of MISFET's are formed in the memory cell area, and low concentration regions 9b of the source/drain regions of a lightly doped drain (LDD) structure are formed in the logic circuit area.

A high performance MISFET can be formed in the logic circuit area by doping As in the low concentration region 9b of MISFET. The source/drain regions 9a

of MISFET in the memory cell area are doped with only P without doping As, so that DRAM having a reduced leak current and good refresh characteristics can be formed.

Processes up to the process illustrated in Fig. 1D will be described. An  $\text{SiO}_2$  film is deposited to a thickness of 80 to 120 nm over the substrate whole surface. For example, the  $\text{SiO}_2$  film is deposited through CVD using  $\text{SiH}_4$  and  $\text{O}_2$ . The memory cell area is covered with a resist pattern 11 to anisotropically etch the  $\text{SiO}_2$  in the logic circuit area. Side wall insulating films 10b are therefore left on the side walls of the gate electrode in the logic circuit area, and an  $\text{SiO}_2$  film 10a is left in the memory cell area.

Next, ion implantation processes are performed to form source/drain regions in the logic circuit area. As ions are implanted in the n-channel MISFET forming area under the conditions of an acceleration energy of 30 to 40 keV and a dose of 2 to  $4 \times 10^{15} \text{ cm}^{-2}$ , and boron (B) ions are implanted in the p-channel MISFET forming area under the conditions of an acceleration energy of 5 to 15 keV and a dose of 2 to  $4 \times 10^{15} \text{ cm}^{-2}$ . During both the ion implantation processes, the memory cell area is covered with the resist pattern. With these ion implantation processes, high concentration regions 12b of source/drain regions of the LDD structure are formed. After these ion implantation processes, a natural oxide film on the silicon surface is removed by using hydrofluoric acid.

As shown in Fig. 1E, cobalt silicide ( $\text{CoSi}_2$ ) films 15 are formed on the surfaces of the gate electrode 8b and high concentration regions 12b. A method of forming the  $\text{CoSi}_2$  film will be described in the following. First, a Co film is deposited through sputtering or the like, covering the whole surface of the substrate. A first thermal annealing is performed at a substrate temperature of 450 to 500°C, and thereafter a second thermal annealing is performed at a substrate temperature of 800 to 900°C. A silicide reaction is therefore performed between the silicon surface and Co film to thereby form the  $\text{CoSi}_2$  film 15. The Co film without the silicide reaction is removed by

using hydrofluoric acid. In this manner, the  $\text{CoSi}_2$  film 15 can be formed in a self-alignment manner only on the silicon exposed surface.

Since the surfaces of the source/drain regions 9a and word lines 8a in the memory cell area are covered with the  $\text{SiO}_2$  film 10a, the silicide reaction will not occur in these areas. Since the high concentration regions 12b of the source/drain regions in the logic circuit area are in contact with the Co film, the silicide reaction occurs at the interface therebetween. Other metals different from Co may be used which form a metal silicide through a silicide reaction with Si, such as Ti.

As shown in Fig. 1F, a borophosphosilicate glass (BPSG) film 18 is deposited to a thickness of 800 to 1200 nm, covering the whole surface of the substrate. For example, the BPSG film 18 is deposited through CVD using a mixture gas of  $\text{SiH}_4$ ,  $\text{B}_2\text{H}_6$ ,  $\text{O}_2$ , and  $\text{PH}_3$  as source gases. A thermal annealing is performed at a substrate temperature of 700 to 850 °C, and thereafter the surface of the BPSG film is planarized through chemical mechanical polishing (CMP).

A contact hole 19 is formed exposing the surface of the source/drain region 9a at the center of the active region 3, by etching the BPSG film 18 through RIE using a mixture gas of  $\text{CF}_4$  and  $\text{CHF}_3$ . A bit line 20 is formed which is connected to the central source/drain region 9a via the contact hole 19. The bit line 20 extends along a direction perpendicular to the word line 82, in the area other than the cross sectional view of Fig.

1F.

A method of forming the bit line 20 will be described in the following. A 50 nm thick polysilicon film doped with P and a 100 nm thick tungsten silicide (WSi) film are deposited covering the whole surface of the substrate. The polysilicon film is deposited through CVD using  $\text{SiH}_4$  as source gas, and the WSi film is deposited through CVD using  $\text{WF}_6$  and  $\text{SiH}_4$  as source gases. Prior to deposition of the polysilicon film, a natural oxide film formed on the bottom of the contact hole 19 may be removed by using

hydrofluoric acid.

The polysilicon film and WSi film are patterned to form the bit line 20. The polysilicon film and WSi film are etched through RIE using  $\text{Cl}_2$  and  $\text{O}_2$ .

As shown in Fig. 1G, a BPSG film 23 is deposited to a thickness of 800 to 1200 nm, covering the whole surface of the substrate. A thermal annealing is performed at a substrate temperature of 700 to 850 °C, and thereafter the surface of the BPSG film 23 is planarized through CMP.

Contact holes 24 are formed exposing the surfaces of the source/drain regions 9a on both sides the central source/drain region 9a in the active region 3.

Storage electrodes 25 are formed which is connected to the source/drain regions 9a via the corresponding contact holes 24. The storage electrode 25 is formed by depositing a polysilicon film doped with P to a thickness of 300 to 800 nm and thereafter patterning this film.

As shown in Fig. 1H, a silicon nitride (SiN) film is deposited to a thickness of 3 to 5 nm, covering the whole surface of the substrate. This SiN film is thermally oxidized at a temperature of 700 to 800 °C to form a capacitor dielectric film 28 made of SiON. An opposing electrode 29 made of polysilicon doped with P and having a thickness of 100 nm is formed covering the capacitor dielectric film 28. The dielectric film 28 and opposing electrode 29 in an area different from the memory cell array area are removed. This two-layer etching is performed through RIE using  $\text{Cl}_2$  and  $\text{O}_2$ .

As shown in Fig. 1I, a BPSG film 30 is deposited to a thickness of 1000 to 1500 nm, covering the whole surface of the substrate. Contact holes 32 are formed exposing a partial surface area of the opposing electrode 29 and a partial surface area of the  $\text{CoSi}_2$  film 15 in the logic circuit area. Although not shown in Fig. 1I, a contact hole exposing a partial surface area of the bit line 20 is formed at the same time.

The inside of the contact hole 32 is embedded with a W plug 35. A method

of forming the W plug 35 will be described in the following. First, a barrier metal layer is deposited by sputtering. For example, the barrier layer has a two-layer structure of a Ti film and a TiN film. A W film is deposited through CVD to a thickness of 300 to 500 nm on the barrier metal layer to fill the inside of the contact hole 32 with W.

- 5 Unnecessary W film and barrier metal layer are removed by CMP to leave only the W plug 35 in the contact hole 32.

A wiring pattern 40 is formed on the BPSG film 30. The wiring pattern has a lamination structure constituted of a barrier metal layer, an aluminum (Al) film, and an antireflection film. For example, the antireflection film is made of TiN.

10 An SiO<sub>2</sub> film 41 is deposited on the BPSG film 30, covering the wiring pattern 40. For example, the SiO<sub>2</sub> film 41 is deposited through CVD using high density plasma. A contact hole is formed in the SiO<sub>2</sub> film 41 and the inside of the contact hole is embedded with a W plug 42. A wiring pattern 43 is formed on the surface of the SiO<sub>2</sub> film 41, and an SiO<sub>2</sub> film 44 is deposited covering the wiring pattern 43.

15 A cover film 45 is deposited covering the SiO<sub>2</sub> film. The cover film 45 has a two-layer structure constituted of an SiO<sub>2</sub> film and an SiN film both formed through plasma CVD.

In the first embodiment described above, the first ion implantation illustrated in Fig. 1A and the second ion implantation illustrated in Fig. 1B are  
20 performed for the gate electrode of MISFET in the memory cell area, i.e., word line 8a. Only the first ion implantation illustrated in Fig. 1A is performed for the gate electrode 8b of n-channel MISFET in the logic circuit area.

The gate electrodes and word lines are used as a mask in the ion implantation process for the source/drain regions described with reference to Figs. 1C and  
25 1D. In this case, impurities are additionally implanted into the word lines 8a and gate electrodes 8b. By taking into consideration this additional ion dose, the doses of the first

and second ion implantation processes are properly selected so that the impurity concentrations in the gate electrodes of MISFET's in the memory cell area and logic circuit area can be within adequate ranges.

In the first embodiment described above, the first ion implantation illustrated in Fig. 1A is performed for both of the memory cell area and the logic circuit area. At the step of the second ion implantation illustrated in Fig. 1B, ion implantation may be performed at a dose of  $8$  to  $15 \times 10^{15} \text{ cm}^{-2}$  without the first ion implantation. In this case, ion implantation for the gate electrode 8b is performed at a same time when ion implantation for a source/drain region of MISFET in the logic circuit area.

Fig. 2A is a graph showing a relation between an impurity dose in a gate electrode and a drain current when a voltage  $2.5 \text{ V}$  is applied to the gate electrode. The abscissa represents an impurity dose in the gate electrode in the unit of " $\times 10^{15} \text{ cm}^{-2}$ ", and the ordinate represents a drain current represented by a value relative to 100 which is the largest drain current among samples used. The thickness of the gate electrode was set to  $180 \text{ nm}$ , implanted impurities were P, and the acceleration energy of ion implantation was set to  $20 \text{ keV}$ . The impurity dose in the channel region was adjusted so that the threshold voltage became  $0.45 \text{ V}$ .

A largest drain current is obtained at about the impurity dose of  $4 \times 10^{15} \text{ cm}^{-2}$ . At the impurity dose larger than this, the drain current reduces. This is because it is necessary to raise the impurity concentration of the channel region as the impurity concentration of the gate electrode increases, in order to prevent the threshold value from being lowered. If the impurity concentration of the gate electrode is too low, the gate electrode is depleted and the characteristics of MISFET are degraded. It is therefore preferable to set the impurity concentration of the gate electrode to about  $4 \times 10^{15} \text{ cm}^{-2}$ .

Fig. 2B is a graph showing a relation between an impurity dose in the gate electrode and a sheet resistance of the gate electrode. The abscissa represents an



impurity dose in the gate electrode in the unit of " $\times 10^{15} \text{cm}^{-2}$ ", and the ordinate represents a sheet resistance in the unit of " $\Omega/\square$ ". The gate electrode thickness, implanted impurities, and acceleration energy were the same as those used for the graph of Fig. 2A.

A sheet resistance of a word line of DRAM is generally  $80 \Omega/\square$  or lower. In order to satisfy this requirement, the impurity dose in the gate electrode is set to about  $1 \times 10^{16} \text{cm}^{-2}$ .

It can be understood from the comparison between Figs. 2A and 2B that the impurity dose necessary for the gate electrode in the logic circuit area is different from that necessary for the gate electrode in the memory cell area. By performing the first ion implantation for the entire polysilicon film 8 and the second ion implantation only for the polysilicon film 8 in the memory cell area, as in the first embodiment, proper impurities can be implanted for the gate electrodes both in the logic circuit area and memory cell area.

Also in the first embodiment, the memory cell area is covered with the  $\text{SiO}_2$  film 10a during the silicide reaction process illustrated in Fig. 1E. It is therefore possible to prevent a metal silicide from being formed on the surfaces of the source/drain regions in the memory cell area. The good data storage characteristics can therefore be realized.

Next, with reference to Figs. 3A to 3F, the second embodiment will be described. In the second embodiment, capacitors are formed in the logic circuit area.

In each drawing, the right side of a cut portion shows a memory cell area, and the left side shows a logic circuit area.

Processes up to the process illustrated in Fig. 3A will be described first.

On the surface of a p-type silicon substrate 50, element separation structures 51 are formed to define active regions 3 in the memory cell array area and logic circuit area.

On the surfaces of the active regions, gate oxide films 52 are formed to a thickness of 5 to 10 nm through thermal oxidation. A first conductive film 53 made of polysilicon is

deposited to a thickness of 100 to 250 nm over the whole surface of the substrate. The first conductive film 53 may be made of amorphous silicon instead of polysilicon.

P ions are implanted into the first conductive film 53 in an n-channel MISFET forming area and a capacitor forming area in the logic circuit area, for example, under the conditions of an acceleration energy of 20 keV and a dose of  $3 \text{ to } 6 \times 10^{15} \text{ cm}^{-2}$ . P and As may be implanted at a total dose of  $3 \text{ to } 6 \times 10^{15} \text{ cm}^{-2}$ . Boron (B) ions are implanted into the first conductive film 53 in a p-channel MISFET forming area in the logic circuit area. Impurities are not necessarily required to be implanted into the first conductive film 53 in the p-channel MISFET forming area. The gate electrode of p-channel MISFET is implanted with p-type impurities at the same time when ions are implanted for forming source/drain regions. After the above ion implantation processes, annealing is performed for activating implanted ions.

After this annealing for activation, the first conductive film 53 in the memory cell area is removed through RIE using a mixture gas of  $\text{Cl}_2$  and  $\text{O}_2$ . After the first conductive film 53 is patterned, the gate oxide film 52 left on the surface of the memory cell area and a natural oxide film formed on the surface of the first conductive film 53 are removed by using hydrofluoric acid.

As shown in Fig. 3B, the surface of the active region in the memory cell area is thermally oxidized to form a second gate oxide film 55 having a thickness of 5 to 10 nm. In this case, the surface of the first conductive layer 53 is also oxidized so that a capacitor dielectric film 56 having a thickness of 10 to 30 nm can be formed at the same time.

As shown in Fig. 3C, a polysilicon film 60, a tungsten silicide (WSi) film 61, and a first SiN film 62 are formed through CVD in this order over the whole surface of the substrate. The polysilicon film 60 is 50 to 100 nm in thickness and doped with P to impart an n-type conductivity. The WSi film 61 and first SiN film 62 have both a

thickness of 100 to 200 nm.

As shown in Fig. 3D, three layers from the first SiN film 62 to the polysilicon layer 60 are patterned to leave word lines 65 in the memory cell area and a capacitor upper electrode 66 in the capacitor forming area in the logic circuit area. The word line 65 and capacitor upper electrode 66 have both a three-layer structure constituted of the polysilicon film 60, WSi film 61, and first SiN film 62. The first SiN film 62 is etched through RIE using a mixture gas of  $\text{CH}_4$ ,  $\text{CHF}_3$ , and Ar, the WSi film 61 is etched through RIE using a mixture gas of  $\text{Cl}_2$  and  $\text{O}_2$ , and the polysilicon film 60 is etched through RIE using a mixture gas of  $\text{Cl}_2$  and  $\text{O}_2$ .

By using the word lines 65 as a mask, P ions are implanted in the memory cell area under the conditions of an acceleration energy of 10 to 30 keV and a dose of  $2 \times 10^{13} \text{cm}^{-2}$ . Source/drain regions 67 are therefore formed on both side of the word line 65 in the memory cell area.

Side wall insulating films 68 made of SiN are formed on the side walls of the word line 65 and capacitor upper electrode 66. The side wall insulating film 68 is formed by depositing an SiN film over the whole surface of the substrate and anisotropically etching this film. This anisotropic etching is performed through RIE using a mixture gas of  $\text{CF}_4$ ,  $\text{CHF}_3$ , and Ar. In this case, the capacitor dielectric film 56 on the first conductive film 53 in the area where the upper capacitor electrode 66 is not formed, is also removed and the upper surface of the first conductive film 53 is exposed.

As shown in Fig. 3E, the first conductive film 53 is patterned to leave a lower capacitor electrode 53a in an area inclusive of the upper capacitor electrode 66 as viewed along a direction normal to the substrate surface and to leave a gate electrode 53b in the n-channel MISFET forming area in the logic circuit area. Although not shown in Fig. 3E, the gate electrode is also left in the p-channel MISFET forming area. The first conductive film 53 is etched through RIE using a mixture gas of  $\text{Cl}_2$  and  $\text{O}_2$ . In some

case, the side wall insulating film 68 on the side wall of the first conductive film 53 is left without being removed. In such a case, when the first conductive film 53 is etched, the boarder area of the first conductive film 53 is covered with a mask pattern to positively leave the first conductive film 53 under the mask pattern.

By using the gate electrode 53b as a mask, As ions are implanted in the n-channel MISFET forming area in the logic circuit area for forming low concentration regions of an LDD structure. The ion implantation conditions are an acceleration energy of 5 to 15 keV and a dose of  $1 \text{ to } 10 \times 10^{13} \text{ cm}^{-2}$ . Similarly, B ions are implanted in the p-channel MISFET forming area under the ion implantation conditions of an acceleration energy of 5 to 15 keV and a dose of  $1 \text{ to } 10 \times 10^{13} \text{ cm}^{-2}$ .

An  $\text{SiO}_2$  film is deposited over the whole surface of the substrate and anisotropically etched to leave side wall insulating films 70b on the side walls of the gate electrode 53a. At this time, side wall insulating films 70a are left on the side walls of the lower capacitor electrode 53a, and side wall insulating films 70d are left on the slanted surfaces of the side wall insulating films 68. In the memory cell area, spaces between word lines 65 are embedded with embedding insulating members 70c.

By using the gate electrode 53b and side wall insulating films 70b as a mask, As ions are implanted in the n-channel MISFET forming area in the logic circuit area for forming high concentration regions of the LDD structure. The ion implantation conditions are an acceleration energy of 30 to 40 keV and a dose of  $2 \text{ to } 4 \times 10^{16} \text{ cm}^{-2}$ . Similarly, B ions are implanted in the p-channel MISFET forming area (not shown) under the ion implantation conditions of an acceleration energy of 5 to 15 keV and a dose of  $2 \text{ to } 4 \times 10^{16} \text{ cm}^{-2}$ . After the ion implantations, annealing for activation is performed to thus form source/drain regions 71 of the LDD structure.

As shown in Fig. 3F,  $\text{CoSi}_2$  films 72 are formed on the upper surfaces of the source/drain regions 71 and gate electrode 53b of MISFET in the logic circuit area. The

CoSi<sub>2</sub> film 72 is formed by a process similar to the process of forming the CoSi<sub>2</sub> film 15 of the first embodiment described with reference to Fig. 1E. During this process, since the surfaces of the source/drain regions 67 in the memory cell area are covered with the embedding insulating members 70c, the CoSi<sub>2</sub> film is not formed on the surfaces of the source/drain regions 67.

By performing processes similar to those of the first embodiment shown in Fig. 1F and following figures, DRAM mixed with logic circuits and containing a capacitor is formed, the capacitor being constituted of the lower capacitor electrode 53a, capacitor dielectric film 56, and upper capacitor electrode 66.

Similar to the first embodiment, also in the second embodiment, a metal silicide film can be formed only in the logic circuit area without forming it in the logic circuit area. In the second embodiment, the upper capacitor electrode 66 is formed by the same process as that for the word lines 65 in the memory cell area, and the lower capacitor electrode 53a is formed by the same process as that for the gate electrode 53b in the logic circuit area. Therefore, a capacitor having a lamination structure of a polysilicon film / an SiO<sub>2</sub> film / a polysilicon film can be formed by suppressing an increase in the number of manufacture processes as much as possible.

Further, as shown in Fig. 3F, the top and side surfaces of the word line 65 are covered with the side wall insulating films 68 made of SiN and first SiN film 62. These side wall insulating films 68 and first SiN film 62 function as the protective films for the WSi film 61 and polysilicon film 60 if the contact hole 19 shown in Fig. 1F and the contact hole 24 shown in Fig. 1G are formed under the conditions that SiN is not substantially etched. It is therefore possible to form the contact holes 19 and 24 in a self-alignment manner.

Still further, since the side wall insulating films 70b on the side walls of the gate electrode 53b in the logic circuit area are made of SiO<sub>2</sub>, it is possible to enhance a hot

carrier resistance of MISFET and reduce parasitic capacitance more than the case where the side wall insulating films are made of SiN. Since the side wall insulating films 70b are formed by a process different from the process of forming the side wall insulating films 68 in the memory cell area, it is possible to set the thickness of the side wall insulating film 70b to a value most suitable for suppressing the short channel effects.

Next, with reference to Figs. 4A to 4F, the third embodiment will be described. In each drawing, the right side of a cut portion shows a memory cell area, and the left side shows a logic circuit area.

Fig. 4A corresponds to Fig. 1C of the first embodiment. A different point from the first embodiment is that an upper  $\text{SiO}_2$  film 80 of about 100 nm thickness is formed on the word line 8a. Processes up to the process illustrated in Fig. 4A will be described by paying attention to processes different from those up to Fig. 1C.

On the substrate formed with element separation structures 2, a polysilicon film and an  $\text{SiO}_2$  film are deposited, and the  $\text{SiO}_2$  film in the logic circuit is removed. Similar to the first embodiment, the polysilicon film contains implanted ions. After the  $\text{SiO}_2$  film in the logic circuit area is removed, the processes similar to the first embodiment are performed to form the substrate shown in Fig. 4A.

In the third embodiment, after ions implanted for forming low density regions 9b of MISFET in the logic circuit area, ions are implanted for forming source/drain regions 9a in the memory cell area.

Processes similar to those up to the process of forming the  $\text{CoSi}_2$  film 15 of the first embodiment shown in Fig. 1E are performed.

As shown in Fig. 4B,  $\text{CoSi}_2$  films 15 are therefore formed on the upper surface of the gate electrode 8b in the logic circuit area and on the upper surfaces of high concentration regions 12b of the source/drain regions. The memory cell area is being covered with an  $\text{SiO}_2$  film which has a thickness of 50 to 120 nm.

As shown in Fig. 1C, a low temperature SiO<sub>2</sub> film 81 is deposited to a thickness of 20 to 50 nm over the whole surface of the substrate. The low temperature SiO<sub>2</sub> film 81 is deposited through CVD at a growth temperature of 700 °C or lower. For example, the SiO<sub>2</sub> film 81 is deposited through plasma CVD at a substrate temperature of about 400 C°. Deposition at a low temperature can prevent the CoSi<sub>2</sub> film 15 from being deteriorated by heat.

As shown in Fig. 4D, the SiO<sub>2</sub> film 10a and low temperature SiO<sub>2</sub> film 81 are anisotropically etched to leave side wall insulating films 82 on the side walls of the lamination structures in the memory cell area each constituted of the word line 8a and upper SiO<sub>2</sub> film 80. In this case, the logic circuit area is covered with a resist pattern. The low temperature SiO<sub>2</sub> film 81 in the logic circuit area is left unetched.

An amorphous silicon film doped with P is deposited through CVD to a thickness of 100 to 200 nm over the whole surface of the substrate. The amorphous silicon film is patterned to leave pads 83 on the source/drain regions 9a in the memory cell area. The pad 83 covers the surface of the source/drain region 9a, the side surfaces of the side wall insulating films 82 on both sides of the source/drain region 9a, and partial top surfaces of the upper SiO<sub>2</sub> films 80.

As shown in Fig. 4E, a BPSG film 18 is deposited over the whole surface of the substrate, and a contact hole 19 is formed therein. Thereafter, a bit line 20 is formed which contacts the pad 83. These processes are similar to those of the first embodiment described with Fig. 1F.

As shown in Fig. 4F, a BPSG film 23 is deposited over the substrate whole surface, a contact hole 24 is formed and thereafter a storage electrode 25 is formed. These processes are similar to those of the first embodiment described with Fig. 1G.

In the third embodiment, when the contact holes 19 and 24 shown in Figs. 4E and 4F are formed, the pads 83 are exposed at the bottoms of the contact holes. The

source/drain regions 9a are not exposed therefore directly to the etching atmosphere, so that any defect in the source/drain regions 9a can be prevented from being formed. It is therefore possible to prevent the data storage characteristics of DRAM from being deteriorated by defects in the source/drain regions 9a.

5 In the first to third embodiments described above, MISFET's in the memory cell area and logic circuit area are formed generally in parallel. A method of forming DRAM formed with logic circuits is known by which after all constituents up to an opposing electrode (e.g., opposing electrode 29 shown in Fig. 1H) are formed in the memory cell area, source/drain regions of MISFET in the logic circuit area are formed. A problem associated with this method is how a bit line in the memory cell area is electrically connected to a wiring pattern in the logic circuit area. Fourth and fifth  
10  
15  
20  
25  
30  
35  
40  
45  
50  
55  
60  
65  
70  
75  
80  
85  
90  
95  
100  
105  
110  
115  
120  
125  
130  
135  
140  
145  
150  
155  
160  
165  
170  
175  
180  
185  
190  
195  
200  
205  
210  
215  
220  
225  
230  
235  
240  
245  
250  
255  
260  
265  
270  
275  
280  
285  
290  
295  
300  
305  
310  
315  
320  
325  
330  
335  
340  
345  
350  
355  
360  
365  
370  
375  
380  
385  
390  
395  
400  
405  
410  
415  
420  
425  
430  
435  
440  
445  
450  
455  
460  
465  
470  
475  
480  
485  
490  
495  
500  
505  
510  
515  
520  
525  
530  
535  
540  
545  
550  
555  
560  
565  
570  
575  
580  
585  
590  
595  
600  
605  
610  
615  
620  
625  
630  
635  
640  
645  
650  
655  
660  
665  
670  
675  
680  
685  
690  
695  
700  
705  
710  
715  
720  
725  
730  
735  
740  
745  
750  
755  
760  
765  
770  
775  
780  
785  
790  
795  
800  
805  
810  
815  
820  
825  
830  
835  
840  
845  
850  
855  
860  
865  
870  
875  
880  
885  
890  
895  
900  
905  
910  
915  
920  
925  
930  
935  
940  
945  
950  
955  
960  
965  
970  
975  
980  
985  
990  
995  
1000  
1005  
1010  
1015  
1020  
1025  
1030  
1035  
1040  
1045  
1050  
1055  
1060  
1065  
1070  
1075  
1080  
1085  
1090  
1095  
1100  
1105  
1110  
1115  
1120  
1125  
1130  
1135  
1140  
1145  
1150  
1155  
1160  
1165  
1170  
1175  
1180  
1185  
1190  
1195  
1200  
1205  
1210  
1215  
1220  
1225  
1230  
1235  
1240  
1245  
1250  
1255  
1260  
1265  
1270  
1275  
1280  
1285  
1290  
1295  
1300  
1305  
1310  
1315  
1320  
1325  
1330  
1335  
1340  
1345  
1350  
1355  
1360  
1365  
1370  
1375  
1380  
1385  
1390  
1395  
1400  
1405  
1410  
1415  
1420  
1425  
1430  
1435  
1440  
1445  
1450  
1455  
1460  
1465  
1470  
1475  
1480  
1485  
1490  
1495  
1500  
1505  
1510  
1515  
1520  
1525  
1530  
1535  
1540  
1545  
1550  
1555  
1560  
1565  
1570  
1575  
1580  
1585  
1590  
1595  
1600  
1605  
1610  
1615  
1620  
1625  
1630  
1635  
1640  
1645  
1650  
1655  
1660  
1665  
1670  
1675  
1680  
1685  
1690  
1695  
1700  
1705  
1710  
1715  
1720  
1725  
1730  
1735  
1740  
1745  
1750  
1755  
1760  
1765  
1770  
1775  
1780  
1785  
1790  
1795  
1800  
1805  
1810  
1815  
1820  
1825  
1830  
1835  
1840  
1845  
1850  
1855  
1860  
1865  
1870  
1875  
1880  
1885  
1890  
1895  
1900  
1905  
1910  
1915  
1920  
1925  
1930  
1935  
1940  
1945  
1950  
1955  
1960  
1965  
1970  
1975  
1980  
1985  
1990  
1995  
2000  
2005  
2010  
2015  
2020  
2025  
2030  
2035  
2040  
2045  
2050  
2055  
2060  
2065  
2070  
2075  
2080  
2085  
2090  
2095  
2100  
2105  
2110  
2115  
2120  
2125  
2130  
2135  
2140  
2145  
2150  
2155  
2160  
2165  
2170  
2175  
2180  
2185  
2190  
2195  
2200  
2205  
2210  
2215  
2220  
2225  
2230  
2235  
2240  
2245  
2250  
2255  
2260  
2265  
2270  
2275  
2280  
2285  
2290  
2295  
2300  
2305  
2310  
2315  
2320  
2325  
2330  
2335  
2340  
2345  
2350  
2355  
2360  
2365  
2370  
2375  
2380  
2385  
2390  
2395  
2400  
2405  
2410  
2415  
2420  
2425  
2430  
2435  
2440  
2445  
2450  
2455  
2460  
2465  
2470  
2475  
2480  
2485  
2490  
2495  
2500  
2505  
2510  
2515  
2520  
2525  
2530  
2535  
2540  
2545  
2550  
2555  
2560  
2565  
2570  
2575  
2580  
2585  
2590  
2595  
2600  
2605  
2610  
2615  
2620  
2625  
2630  
2635  
2640  
2645  
2650  
2655  
2660  
2665  
2670  
2675  
2680  
2685  
2690  
2695  
2700  
2705  
2710  
2715  
2720  
2725  
2730  
2735  
2740  
2745  
2750  
2755  
2760  
2765  
2770  
2775  
2780  
2785  
2790  
2795  
2800  
2805  
2810  
2815  
2820  
2825  
2830  
2835  
2840  
2845  
2850  
2855  
2860  
2865  
2870  
2875  
2880  
2885  
2890  
2895  
2900  
2905  
2910  
2915  
2920  
2925  
2930  
2935  
2940  
2945  
2950  
2955  
2960  
2965  
2970  
2975  
2980  
2985  
2990  
2995  
3000  
3005  
3010  
3015  
3020  
3025  
3030  
3035  
3040  
3045  
3050  
3055  
3060  
3065  
3070  
3075  
3080  
3085  
3090  
3095  
3100  
3105  
3110  
3115  
3120  
3125  
3130  
3135  
3140  
3145  
3150  
3155  
3160  
3165  
3170  
3175  
3180  
3185  
3190  
3195  
3200  
3205  
3210  
3215  
3220  
3225  
3230  
3235  
3240  
3245  
3250  
3255  
3260  
3265  
3270  
3275  
3280  
3285  
3290  
3295  
3300  
3305  
3310  
3315  
3320  
3325  
3330  
3335  
3340  
3345  
3350  
3355  
3360  
3365  
3370  
3375  
3380  
3385  
3390  
3395  
3400  
3405  
3410  
3415  
3420  
3425  
3430  
3435  
3440  
3445  
3450  
3455  
3460  
3465  
3470  
3475  
3480  
3485  
3490  
3495  
3500  
3505  
3510  
3515  
3520  
3525  
3530  
3535  
3540  
3545  
3550  
3555  
3560  
3565  
3570  
3575  
3580  
3585  
3590  
3595  
3600  
3605  
3610  
3615  
3620  
3625  
3630  
3635  
3640  
3645  
3650  
3655  
3660  
3665  
3670  
3675  
3680  
3685  
3690  
3695  
3700  
3705  
3710  
3715  
3720  
3725  
3730  
3735  
3740  
3745  
3750  
3755  
3760  
3765  
3770  
3775  
3780  
3785  
3790  
3795  
3800  
3805  
3810  
3815  
3820  
3825  
3830  
3835  
3840  
3845  
3850  
3855  
3860  
3865  
3870  
3875  
3880  
3885  
3890  
3895  
3900  
3905  
3910  
3915  
3920  
3925  
3930  
3935  
3940  
3945  
3950  
3955  
3960  
3965  
3970  
3975  
3980  
3985  
3990  
3995  
4000  
4005  
4010  
4015  
4020  
4025  
4030  
4035  
4040  
4045  
4050  
4055  
4060  
4065  
4070  
4075  
4080  
4085  
4090  
4095  
4100  
4105  
4110  
4115  
4120  
4125  
4130  
4135  
4140  
4145  
4150  
4155  
4160  
4165  
4170  
4175  
4180  
4185  
4190  
4195  
4200  
4205  
4210  
4215  
4220  
4225  
4230  
4235  
4240  
4245  
4250  
4255  
4260  
4265  
4270  
4275  
4280  
4285  
4290  
4295  
4300  
4305  
4310  
4315  
4320  
4325  
4330  
4335  
4340  
4345  
4350  
4355  
4360  
4365  
4370  
4375  
4380  
4385  
4390  
4395  
4400  
4405  
4410  
4415  
4420  
4425  
4430  
4435  
4440  
4445  
4450  
4455  
4460  
4465  
4470  
4475  
4480  
4485  
4490  
4495  
4500  
4505  
4510  
4515  
4520  
4525  
4530  
4535  
4540  
4545  
4550  
4555  
4560  
4565  
4570  
4575  
4580  
4585  
4590  
4595  
4600  
4605  
4610  
4615  
4620  
4625  
4630  
4635  
4640  
4645  
4650  
4655  
4660  
4665  
4670  
4675  
4680  
4685  
4690  
4695  
4700  
4705  
4710  
4715  
4720  
4725  
4730  
4735  
4740  
4745  
4750  
4755  
4760  
4765  
4770  
4775  
4780  
4785  
4790  
4795  
4800  
4805  
4810  
4815  
4820  
4825  
4830  
4835  
4840  
4845  
4850  
4855  
4860  
4865  
4870  
4875  
4880  
4885  
4890  
4895  
4900  
4905  
4910  
4915  
4920  
4925  
4930  
4935  
4940  
4945  
4950  
4955  
4960  
4965  
4970  
4975  
4980  
4985  
4990  
4995  
5000  
5005  
5010  
5015  
5020  
5025  
5030  
5035  
5040  
5045  
5050  
5055  
5060  
5065  
5070  
5075  
5080  
5085  
5090  
5095  
5100  
5105  
5110  
5115  
5120  
5125  
5130  
5135  
5140  
5145  
5150  
5155  
5160  
5165  
5170  
5175  
5180  
5185  
5190  
5195  
5200  
5205  
5210  
5215  
5220  
5225  
5230  
5235  
5240  
5245  
5250  
5255  
5260  
5265  
5270  
5275  
5280  
5285  
5290  
5295  
5300  
5305  
5310  
5315  
5320  
5325  
5330  
5335  
5340  
5345  
5350  
5355  
5360  
5365  
5370  
5375  
5380  
5385  
5390  
5395  
5400  
5405  
5410  
5415  
5420  
5425  
5430  
5435  
5440  
5445  
5450  
5455  
5460  
5465  
5470  
5475  
5480  
5485  
5490  
5495  
5500  
5505  
5510  
5515  
5520  
5525  
5530  
5535  
5540  
5545  
5550  
5555  
5560  
5565  
5570  
5575  
5580  
5585  
5590  
5595  
5600  
5605  
5610  
5615  
5620  
5625  
5630  
5635  
5640  
5645  
5650  
5655  
5660  
5665  
5670  
5675  
5680  
5685  
5690  
5695  
5700  
5705  
5710  
5715  
5720  
5725  
5730  
5735  
5740  
5745  
5750  
5755  
5760  
5765  
5770  
5775  
5780  
5785  
5790  
5795  
5800  
5805  
5810  
5815  
5820  
5825  
5830  
5835  
5840  
5845  
5850  
5855  
5860  
5865  
5870  
5875  
5880  
5885  
5890  
5895  
5900  
5905  
5910  
5915  
5920  
5925  
5930  
5935  
5940  
5945  
5950  
5955  
5960  
5965  
5970  
5975  
5980  
5985  
5990  
5995  
6000  
6005  
6010  
6015  
6020  
6025  
6030  
6035  
6040  
6045  
6050  
6055  
6060  
6065  
6070  
6075  
6080  
6085  
6090  
6095  
6100  
6105  
6110  
6115  
6120  
6125  
6130  
6135  
6140  
6145  
6150  
6155  
6160  
6165  
6170  
6175  
6180  
6185  
6190  
6195  
6200  
6205  
6210  
6215  
6220  
6225  
6230  
6235  
6240  
6245  
6250  
6255  
6260  
6265  
6270  
6275  
6280  
6285  
6290  
6295  
6300  
6305  
6310  
6315  
6320  
6325  
6330  
6335  
6340  
6345  
6350  
6355  
6360  
6365  
6370  
6375  
6380  
6385  
6390  
6395  
6400  
6405  
6410  
6415  
6420  
6425  
6430  
6435  
6440  
6445  
6450  
6455  
6460  
6465  
6470  
6475  
6480  
6485  
6490  
6495  
6500  
6505  
6510  
6515  
6520  
6525  
6530  
6535  
6540  
6545  
6550  
6555  
6560  
6565  
6570  
6575  
6580  
6585  
6590  
6595  
6600  
6605  
6610  
6615  
6620  
6625  
6630  
6635  
6640  
6645  
6650  
6655  
6660  
6665  
6670  
6675  
6680  
6685  
6690  
6695  
6700  
6705  
6710  
6715  
6720  
6725  
6730  
6735  
6740  
6745  
6750  
6755  
6760  
6765  
6770  
6775  
6780  
6785  
6790  
6795  
6800  
6805  
6810  
6815  
6820  
6825  
6830  
6835  
6840  
6845  
6850  
6855  
6860  
6865  
6870  
6875  
6880  
6885  
6890  
6895  
6900  
6905  
6910  
6915  
6920  
6925  
6930  
6935  
6940  
6945  
6950  
6955  
6960  
6965  
6970  
6975  
6980  
6985  
6990  
6995  
7000  
7005  
7010  
7015  
7020  
7025  
7030  
7035  
7040  
7045  
7050  
7055  
7060  
7065  
7070  
7075  
7080  
7085  
7090  
7095  
7100  
7105  
7110  
7115  
7120  
7125  
7130  
7135  
7140  
7145  
7150  
7155  
7160  
7165  
7170  
7175  
7180  
7185  
7190  
7195  
7200  
7205  
7210  
7215  
7220  
7225  
7230  
7235  
7240  
7245  
7250  
7255  
7260  
7265  
7270  
7275  
7280  
7285  
7290  
7295  
7300  
7305  
7310  
7315  
7320  
7325  
7330  
7335  
7340  
7345  
7350  
7355  
7360  
7365  
7370  
7375  
7380  
7385  
7390  
7395  
7400  
7405  
7410  
7415  
7420  
7425  
7430  
7435  
7440  
7445  
7450  
7455  
7460  
7465  
7470  
7475  
7480  
7485  
7490  
7495  
7500  
7505  
7510  
7515  
7520  
7525  
7530  
7535  
7540  
7545  
7550  
7555  
7560  
7565  
7570  
7575  
7580  
7585  
7590  
7595  
7600  
7605  
7610  
7615  
7620  
7625  
7630  
7635  
7640  
7645  
7650  
7655  
7660  
7665  
7670  
7675  
7680  
7685  
7690  
7695  
7700  
7705  
7710  
7715  
7720  
7725  
7730  
7735  
7740  
7745  
7750  
7755  
7760  
7765  
7770  
7775  
7780  
7785  
7790  
7795  
7800  
7805  
7810  
7815  
7820  
7825  
7830  
7835  
7840  
7845  
7850  
7855  
7860  
7865  
7870  
7875  
7880  
7885  
7890  
7895  
7900  
7905  
7910  
7915  
7920  
7925  
7930  
7935  
7940  
7945  
7950  
7955  
7960  
7965  
7970  
7975  
7980  
7985  
7990  
7995  
8000  
8005  
8010  
8015  
8020  
8025  
8030  
8035  
8040  
8045  
8050  
8055  
8060  
8065  
8070  
8075  
8080  
8085  
8090  
8095  
8100  
8105  
8110  
8115  
8120  
8125  
8130  
8135  
8140  
8145  
8150  
8155  
8160  
8165  
8170  
8175  
8180  
8185  
8190  
8195  
8200  
8205  
8210  
8215  
8220  
8225  
8230  
8235  
8240  
8245  
8250  
8255  
8260  
8265  
8270  
8275  
8280  
8285  
8290  
8295  
8300  
8305  
8310  
8315  
8320  
8325  
8330  
8335  
8340  
8345  
8350  
8355  
8360  
8365  
8370  
8375  
8380  
8385  
8390  
8395  
8400  
8405  
8410  
8415  
8420  
8425  
8430  
8435  
8440  
8445  
8450  
8455  
8460  
8465  
8470  
8475  
8480  
8485  
8490  
8495  
8500  
8505  
8510  
8515  
8520  
8525  
8530  
8535  
8540  
8545  
8550  
8555  
8560  
8565  
8570  
8575  
8580  
8585  
8590  
8595  
8600  
8605  
8610  
8615  
8620  
8625  
8630  
8635  
8640  
8645  
8650  
8655  
8660  
8665  
8670  
8675  
8680  
8685  
8690  
8695  
8700  
8705  
8710  
8715  
8720  
8725  
8730  
8735  
8740  
8745  
8750  
8755  
8760  
8765  
8770  
8775  
8780  
8785  
8790  
8795  
8800  
8805  
8810  
8815  
8820  
8825  
8830  
8835  
8840  
8845  
8850  
8855  
8860  
8865  
8870  
8875  
8880  
8885  
8890  
8895  
8900  
8905  
8910  
8915  
8920  
8925  
8930  
8935  
8940  
8945  
8950  
8955  
8960  
8965  
8970  
8975  
8980  
8985  
8990  
8995  
9000  
9005  
9010  
9015  
9020  
9025  
9030  
9035  
9040  
9045  
9050  
9055  
9060  
9065  
9070  
9075  
9080  
9085  
9090  
9095  
9100  
9105  
9110  
9115  
9120  
9125  
9130  
9135  
9140  
9145  
9150  
9155  
9160  
9165  
9170  
9175  
9180  
9185  
9190  
9195  
9200  
9205  
9210  
9215  
9220  
9225  
9230  
9235  
9240  
9245  
9250  
9255  
9260  
9265  
9270  
9275  
9280  
9285  
9290  
9295  
9300  
9305  
9310  
9315  
9320  
9325  
9330  
9335  
9340  
9345  
9350  
9355  
9360  
9365  
9370  
9375  
9380  
9385  
9390  
9395  
9400  
9405  
9410  
9415  
9420  
9425  
9430  
9435  
9440  
9445  
9450  
9455  
9460  
9465  
9470  
9475  
9480  
9485  
9490  
9495  
9500  
9505  
9510  
9515  
9520  
9525  
9530  
9535  
9540  
9545  
9550  
9555  
9560  
9565  
9570  
9575  
9580  
9585  
9590  
9595  
9600  
9605  
9610  
9615  
9620  
9625  
9630  
9635  
9640  
9645  
9650  
9655  
9660  
9665  
9670  
9675  
9680  
9685  
9690  
9695  
9700  
9705  
9710  
9715  
9720  
9725  
9730  
9735  
9740  
9745  
9750  
9755  
9760  
9765  
9770  
9775  
9780  
9785  
9790  
9795  
9800  
9805  
9810  
9815  
9820  
9825  
9830  
9835  
9840  
9845  
9850  
9855  
9860  
9865  
9870  
9875  
9880  
9885  
9890  
9895  
9900  
9905  
9910  
9915  
9920  
9925  
9930  
9935  
9940  
9945  
9950  
9955  
9960  
9965  
9970  
9975  
9980  
9985  
9990  
9995  
10000  
10005  
10010  
10015  
10020  
10025  
10030  
10035  
10040  
10045  
10050  
10055  
10060  
10065  
10070  
10075  
10080  
10085  
10090  
10095  
10100  
10105  
10110  
10115  
10120  
10125  
10130  
10135  
10140  
10145  
10150  
10155  
10160  
10165  
10170  
10175  
10180  
10185  
10190  
10195  
10200  
10205  
10210  
10215  
10220  
10225  
10230  
10235  
10240  
10245  
10250  
10



A resist pattern 97 is formed covering the surface of the opposing electrode 96 in the memory cell area. The boarder of the resist pattern protrudes toward the logic circuit area by about 0.2  $\mu\text{m}$  from the front end of the bit line 93. By using the resist pattern 97 as a mask, the opposing electrode 96 deposited in the logic circuit is removed.

5 The opposing electrode 96 is removed thorough isotropic etching using chlorine containing gas.

The opposing electrode 96 is also side-etched and the boarder thereof retracts from the boarder of the resist pattern 97. The depth of side-etch is set to about 1 to 1.5  $\mu\text{m}$ . Namely, the border of the opposing electrode 96 retracts from the front end of the bit line 93 by about 0.8 to 1.3  $\mu\text{m}$ .

10 After the opposing electrode 96 is removed, the interlayer insulating films 99 and 98 in the logic circuit area are removed by using the resist pattern 97 as a mask.

15 The interlayer insulating films 99 and 98 are removed through anisotropic RIE. In order to stop anisotropic RIE etching with good reproductivity, the surfaces of the gate electrode 100, side wall insulating films 101, and silicon substrate 90 may be covered with a thin SiN film. If this thin SiN film is used, it is removed after the interlayer insulating films 99 and 98 are removed.

P ions are implanted in the logic circuit area by using as a mask the gate electrode 100 and side wall insulating films 101. The ion implantation conditions are 20 the same as those used for forming the high concentration regions 12b of the first embodiment shown in Fig. 1D. After this ion implantation, the resist pattern 97 is removed.

25 As shown in Fig. 5B, an interlayer insulating film 105 of BPSG is deposited over the substrate whole surface, and the surface thereof is planarized through CMP. A contact hole 106 is formed thorough the interlayer insulating films 105 and 99 to expose the partial top surface of the bit line 93. The contact hole 106 is formed at the position

away from the boarder of the opposing electrode 96 toward the logic circuit area. Since the boarder of the opposing electrode 96 retracts by about 0.8 to 1.3  $\mu\text{m}$  from the front end of the bit line 93, the contact hole 106 can be formed without being in contact with the opposing electrode 93. In the logic circuit area, a wiring pattern 107 is formed on the interlayer insulating film 105. This wiring pattern 107 is connected via the contact hole 106 to the bit line 93.

In the fourth embodiment, the boarder of the opposing electrode 96 is defined by side-etch, and a dedicated photomask for defining the boarder of the opposing electrode 96 is not used. Namely, the boarder of the opposing electrode 96 can be defined by using only the resist pattern which defines the boarder line between the memory cell area and logic circuit area.

Next, with reference to Figs. 6A and 6B, the fifth embodiment will be described. As shown in Fig. 6A, the memory cell area of a silicon substrate 90 has a DRAM circuit formed therein. The structure of the DRAM circuit is the same as that of the fourth embodiment shown in Fig. 5A.

An element separation structure 110 defines a boarder between the memory cell area and logic circuit area. On the surface of the element separation structure 110, an interconnect wiring pattern 111 is formed in correspondence with each bit line 93. The interconnect wiring pattern 111 is formed by the same processes as those used for a word line 92. Each bit line 93 is connected to the interconnect wiring pattern 110 via a contact hole formed through an interlayer insulating film 98 at the position near the front end of the bit line 93.

The surface of an opposing electrode 96 in the memory cell area is covered with a resist pattern 97. By using this resist pattern 97 as a mask, the opposing electrode 96 and interlayer insulating film 99 in the logic circuit area are removed. A partial surface area of the interconnect wiring pattern 111 is exposed in the logic circuit

area. The surfaces of the gate electrode 100, side wall insulating films 101, and interconnect wiring pattern 111 may be covered with an SiN film which is used as an etching stopper layer. Similar to the processes of the fourth embodiment shown in Fig. 5A, P ions are implanted in the logic circuit area.

5 As shown in Fig. 6B, an interlayer insulating film 105 of BPSG is deposited over the substrate whole surface, and the surface thereof is planarized through CMP. A contact hole 106 is formed thorough the interlayer insulating film 105 to expose the partial top surface of the interconnect wiring pattern 111. The contact hole 106 is formed at the position away from the boarder of the opposing electrode 96 toward the logic circuit area. Since the interconnect wiring pattern 111 extends to the logic circuit area, the contact hole 106 can be formed without being in contact with the opposing electrode 93.

10 In the logic circuit area, a wiring pattern 107 is formed on the interlayer insulating film 105. This wiring pattern 107 is connected via the contact hole 106 to the bit line 93.

15 In the fifth embodiment, the bit line 93 is connected to the wiring pattern 107 via the interconnect wiring pattern 111. Therefore, similar to the fourth embodiment, the bit line 93 and wiring pattern 107 can be connected with good reproductivity by using only the resist pattern 97 which defines the boarder between the logic circuit area and memory cell area.

20 The present invention has been described in connection with the preferred embodiments. The invention is not limited only to the above embodiments. It is apparent that various modifications, improvements, combinations, and the like can be made by those skilled in the art.